

ROBUS®

VEGAS 12V/24V, IP20, CONSTANT VOLTAGE DRIVER, TRIAC DIMMABLE

RVA3012DU-PSU RVA3024DU-PSU

PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES.

! Electrical products can cause death or injury, or damage to property. If in any doubt about the installation or use of this product, consult a competent electrician
Note:

Product technical information and specification may change over time without prior notification. For the latest technical information please visit our web site www.robust.com.au

-20°C < Ta < +40°C, 220-240V ~ 50/60Hz, Class II, IP20
 Suitable for mounting on a normally flammable surface.
 See website for compatible dimmer list: www.robust.com.au

	Output load	Output Current	Output Voltage	PF	Efficiency	Warranty
RVA3012DU-PSU	30W Max.	2.5A Max.	12V DC	≥ 0.9	≥ 80%	3 Years
RVA3024DU-PSU	30W Max.	1.25A Max.	24V DC	≥ 0.9	≥ 80%	3 Years

Installation

- 1 Ensure mains supply is switched off before commencing work.
 - 2 Consider total power of LED strip and choose the appropriate driver code.
- Connection options:

- A: Connect supply to driver. Brown Live from dimmer to L and Blue Neutral to N as per figure 2. Connect secondary cable Red V+ and Black V- to positive and negative on LED strip.
 B: In order to increase the length of LED strips, choose the Vegas amplifier

The Installation must be carried out by a qualified electrician

LED Group Australasia
 9/210 Queensport Road North
 Murarrie
 QLD 4172
 Australia
 Tel: 07 3890 5444
 Fax: 07 3890 4777
 Email: purchases@robust.com
 Website: www.robust.com.au

LED Group
 Crowe Hogwarth
 72 Trafalgar Square
 NELSON 7010
 New Zealand
 Tel: +64 0508 533 335
 Email: nz_purchases@robust.com
 Website: www.robustled.co.nz

