

# ROBUS®

QUALITY PRODUCTS BY LED GROUP

**60W STREEX IP66 LED STREETLIGHT, 4000K  
C/W 10M FLEX, S CLASS BEAM, DARK GREY**

**RSE6040S-25**

EN

**PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION  
AND RETAIN FOR FUTURE REFERENCES.**

**! Electrical products can cause death or injury, or damage to property.  
If in any doubt about the installation or use of this product, consult a  
competent electrician**

**Note:**

**Product technical information and specification may change over time  
without prior notification. For the latest technical information please  
visit our web site [www.ledgrouprobust.com](http://www.ledgrouprobust.com) or [robustdirect.com](http://robustdirect.com)**

-25°C < Ta < +40°C, 220-240V ~ 50/60Hz, Class I, IP66

## Installation

1. Ensure mains supply is switched off before commencing work.
2. Select suitable location and mounting for luminaire.
3. Safety note! The power supply cord must not be exposed to avoid mechanical damage.
4. Open the upper cover by releasing the fastening clips on the side of fitting body.
5. To change from side entry to post mount configuration, unscrew support clamps at back of fitting with appropriately sized allen key and rotate the mounting to point downwards from fitting. Replace screw clamps and firmly tighten.
6. To adjust the pitch angle up or down, untighten support clamp screws at the back of the fitting using allen key. Select pitch angle on guide at back of fitting and tighten screws in selected position.
7. Run the 10m cable in to the Ø76mm spigot and down to connection point / cut out : Live – Brown, Neutral – Blue and, Yellow/Green - Earth.
8. place the fitting mounting on to the spigot. Ensure the fitting is mounted correctly using spirit level inside fitting.
9. Tighten the bolts on the two sides of the mounting.
10. Refit the upper cover by releasing the stoping clip on the top of fitting and engage the fastening clips.

## Information for the Product user:

1. Please note the requirement to dispose of Waste Electrical & Electronic Equipment separately from household waste (WEEE marked with crossed out wheelie bin symbol).
2. Please consider your role in contributing to re-use and recycling by returning this product at end of life to a collection centre for waste electrical equipment or a Civic Amenity site, or to a retail outlet from which you are purchasing a replacement.
3. This equipment may contain substances that are hazardous to health and the environment if disposed of carelessly. It is important that it is separated from normal household waste and recycled in the WEEE chain
4. The "crossed out wheelie bin symbol" on a product indicates this equipment must not be disposed of in normal household waste, but should be disposed of according to local WEEE regulations

**The Installation must be carried out by a qualified electrician**

LED Group  
Western Retail Park  
Nangor Road  
Dublin 12  
Ireland

Tel: +353 1 7099000  
Fax: +353 1 7099060  
Email: [info@ledgrouprobust.com](mailto:info@ledgrouprobust.com)  
Website: [www.ledgrouprobust.com](http://www.ledgrouprobust.com)

