

PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES. ! Electrical products can cause death or injury, or damage to property. If in any doubt about the installation or use of this product, consult a competent electrician.

Note: If fitting you are adding DALI driver to is not listed, then visit our website / or contact our Technical department for further details.

Please visit our web site www.robus.com and www.robus.com.au

| EU Items | Description | Corresponding driver current level | Choose the DIP switch on Dali driver | | | | |
|-------------------|----------------------------------|------------------------------------|--------------------------------------|----------------------------------|----------------------------------|----------------------------------|----------------------------------|
| | | | 1 | 2 | 3 | 4 | 5 |
| R18230DL-01 | 18W ETERNITY DOWNLIGHT | 450mA | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R18230DLWW-01 | 18W ETERNITY DOWNLIGHT | 450mA | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RMP20WCCT3DL-01 | 20W MORPH DOWNLIGHT | 450mA | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R25230DL-01 | 25W ETERNITY DOWNLIGHT | 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R25230DLWW-01 | 25W ETERNITY DOWNLIGHT | 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RMP30WCCT3DL-01 | 30W MORPH DOWNLIGHT | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RSP30406060G-01 | 30W SPACE UGR PANEL 60X60 | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RSP30506060G-01 | 30W SPACE UGR PANEL 60X60 | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RSP30403012G-01 | 30W SPACE UGR PANEL 30X120 | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RSP30503012G-01 | 30W SPACE UGR PANEL 30X120 | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RAM40406060-01 | 40W ATMOS PANEL 60X60 | 850mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RAM40506060-01 | 40W ATMOS PANEL 60X60 | 850mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RAM40306060-01 | 40W ATMOS PANEL 60X60 | 850mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RSP40406060G-01 | 40W SPACE UGR PANEL 60X60 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RSP40506060G-01 | 40W SPACE UGR PANEL 60X60 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RSP40403012G-01 | 40W SPACE UGR PANEL 30X120 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RSP40503012G-01 | 40W SPACE UGR PANEL 30X120 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RAM40403012-01 | 40W ATMOS PANEL 30X120 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RGA2040-01 | GRANADA 20W LED DOWNLIGHT | 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RGA2840-01 | GRANADA 28W LED DOWNLIGHT | 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RMP20WCCT3DL-01 | MORPH 20W CCT3 LED downlight | 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RMP30WCCT3DL-01 | MORPH 30W CCT3 LED downlight | 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RVR1840-01 | VIRTUE 18W LED Downlight | 450mA | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RVR2440-01 | VIRTUE 24W LED Downlight | 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R225LEDC30-01 | SUN 18W LED circular panel | 550mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R225LEDC40-01 | SUN 18W LED circular panel | 550mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R300LEDC40-01 | SUN 24W LED circular panel | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RMR1824X0-01 | Mira dual wattages LED downlight | 18W: 350mA 24W: 500mA | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RMR3040X0-01 | Mira dual wattages LED downlight | 30W: 650mA 40W: 850mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RDL40406060-01 | 40W Dallas LED panel | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RDL40406060UGR-01 | 40W Dallas LED UGR panel | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| R225LEDC30N-01 | Sun 18W LED circular panel | 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R225LEDC40N-01 | Sun 18W LED circular panel | 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R300LEDC40N-01 | SUN 24W LED circular panel | 650mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |

The DIP switch on dali driver

| mA | 1 | 2 | 3 | 4 | 5 |
|--------|----------------------------------|----------------------------------|----------------------------------|----------------------------------|----------------------------------|
| 350mA | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 400mA | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 450mA | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 550mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 600mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 650mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 800mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 850mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 900mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 950mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| 1050mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| 1100mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |



LED Group
Crowe Hogwarth
72 Trafalgar Square
NELSON 7010
New Zealand
Tel: +64 0508 533 335
Email: nz_purchases@robus.com
Website: www.robusled.co.nz

LED Group Australia Pty Limited
Suite B, 2 Pittwin Road
Capalaba
Queensland 4157
Australia
Tel: 07 3890 5444
Fax: 07 3890 4777
Email: purchases@robus.com
Website: www.robus.com.au

LED Group
Western Retail Park
Nangor Road
Dublin 12 D12 E7VP
Ireland
Tel: +353 1 7099000
Fax: +353 1 7099060
Email: info@robus.com
Website: www.robus.com

| AU Items | Description | Corresponding driver current level | Choose the DIP switch on Dali driver | | | | |
|------------------|------------------------|------------------------------------|--------------------------------------|----------------------------------|----------------------------------|----------------------------------|----------------------------------|
| | | | 1 | 2 | 3 | 4 | 5 |
| RMP20WDLCCCT3-01 | 20W MORPH DOWNLIGHT | 450mA | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R18230DLAU-01 | 18W ETERNITY DOWNLIGHT | 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R18230DLWWAU-01 | 18W ETERNITY DOWNLIGHT | 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RMP30WDLCCCT3-01 | 30W MORPH DOWNLIGHT | 650mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R25230DLAU-01 | 25W ETERNITY DOWNLIGHT | 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| R25230DLWWAU-01 | 25W ETERNITY DOWNLIGHT | 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| RP30403012-01 | 30W SPACE PANEL 30X120 | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RP30653012-01 | 30W SPACE PANEL 30X120 | 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| RP40406060-01 | 40W SPACE PANEL 60X60 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RP40656060-01 | 40W SPACE PANEL 60X60 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RP40403012-01 | 40W SPACE PANEL 30X120 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| RP40653012-01 | 40W SPACE PANEL 30X120 | 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |

The DIP switch on dali driver

| mA | 1 | 2 | 3 | 4 | 5 |
|--------|----------------------------------|----------------------------------|----------------------------------|----------------------------------|----------------------------------|
| 350mA | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 400mA | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 450mA | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 500mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 550mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 600mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 650mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 700mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| 750mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 800mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 850mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 900mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> |
| 950mA | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| 1000mA | <input checked="" type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| 1050mA | <input type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| 1100mA | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |



LED Group
 Crowe Hogwarth
 72 Trafalgar Square
 NELSON 7010
 New Zealand
 Tel: +64 0508 533 335
 Email: nz_purchases@robus.com
 Website: www.robusled.co.nz

LED Group Australia Pty Limited
 Suite B, 2 Pittwin Road
 Capalaba
 Queensland 4157
 Australia
 Tel: 07 3890 5444
 Fax: 07 3890 4777
 Email: purchases@robus.com
 Website: www.robus.com.au

LED Group
 Western Retail Park
 Nangor Road
 Dublin 12 D12 E7VP
 Ireland
 Tel: +353 1 7099000
 Fax: +353 1 7099060
 Email: info@robus.com
 Website: www.robus.com