

## VEGAS 24V, IP67, CONSTANT VOLTAGE DRIVER, NON-DIMMABLE

**RVA10024IP67-PSU    RVA32024IP67-PSU**

**PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES.**

**! Electrical products can cause death or injury, or damage to property. If in any doubt about the installation or use of this product, consult a competent electrician**

**Note:**

**Product technical information and specification may change over time without prior notification. For the latest technical information please visit our web site [www.ledgrouprobust.com.au](http://www.ledgrouprobust.com.au)**

-20°C < Ta < +40°C, 220-240V ~ 50/60Hz, Class I, IP67  
Luminaire is non-dimmable  
Suitable for mounting on a normally flammable surface.

	Output load	Output Current	Output Voltage	PF	Efficiency	Warranty
RVA10024IP67-PSU	100W Max.	4.17A Max.	24V DC	≥ 0.95	≥ 85%	3 Years
RVA32024IP67-PSU	320W Max.	13.4A Max.	24V DC	≥ 0.90	≥ 90%	3 Years

### Installation

- 1 Ensure mains supply is switched off before commencing work.
- 2 Consider total power of LED strip and choose the appropriate driver code.
- 3 To retain IP rating, make connections in an IP rated enclosure.
- 4 Connect driver primary cables live (L: Brown), neutral (N: Blue) and Earth (E: Yellow/Green) to power supply.
- 5 Connect secondary cable white V+ and Black V- to positive and negative on LED strip or Vegas LED controller and amplifier.

Note: Increase the length of LED strips will increase the load on the driver. Consider the potential load on the driver and chose accordingly.

### Information for the Product user:

1. Please note the requirement to dispose of Waste Electrical & Electronic Equipment separately from household waste (WEEE marked with crossed out wheelie bin symbol).
2. Please consider your role in contributing to re-use and recycling by returning this product at end of life to a collection centre for waste electrical equipment or a Civic Amenity site, or to a retail outlet from which you are purchasing a replacement.
3. This equipment may contain substances that are hazardous to health and the environment if disposed of carelessly. It is important that it is separated from normal household waste and recycled in the WEEE chain
4. The "crossed out wheelie bin symbol" on a product indicates this equipment must not be disposed of in normal household waste, but should be disposed of according to local WEEE regulations

**The Installation must be carried out by a qualified electrician**

LED Group Australasia  
9/210 Queensland Road North  
Murarrie  
QLD 4172  
Australia

Tel: 07 3890 5444  
Fax: 07 3890 4777  
Email: [purchases@ledgrouprobust.com.au](mailto:purchases@ledgrouprobust.com.au)  
Website: [www.ledgrouprobust.com.au](http://www.ledgrouprobust.com.au)

